


Wireless Smart Gateway

User manual



Hafele Smart Living



Please read the instruction manual carefully before using the product

1. Product specification


Product name	Wireless smart gateway
Power specification	DC5V 1A Micro USB
Temperature detection range	-10°C - 45°C
Humidity detection range	5% - 90% RH (No condensation)
Wireless connection	Zigbee 3.0 Wifi 2.4G (IEEE802.11b/g /n)

2. Packing list

- Wireless smart gateway x1
- Power cable x1
- Instruction manual x1

3. Product description

The smart gateway is the control center of the smart devices. Users can design and implement smart application scenarios by adding smart devices.




Indicator light:

- *Solid blue & flashing red: Waiting for pairing the gateway to the network.*
- *Solid red & flashing blue: Waiting for pairing Zigbee end devices to the gateway.*
- *Solid red: Normal working.*

5. Preparation for use

- Connect power to smart gateway.
- Mobile phone is connected to 2.4GHz Wifi



Ensure that the smart phone is within the same Wifi network of the Smart Gateway to ensure an effective connection between the smart phone and the Smart Gateway.

5. Preparation for use

HÄFELE

- Download and open the APP

In the App Store, search for "Hafele Smart Living" or scan the QR code on the manual to download and install the smart APP.

If you are downloading this App for the first time, please tap the "Sign up" button to register your account. If you are already have an account, click the "Login" button





Hafele Smart Living

6. Set up and Pairing

HÄFELE

Power-on to Smart Gateway. The indicator light will flash, if the indicator is not flashing, Press Reset button and hold for 5 seconds until the indicator light starts to flash. The Smart Gateway is now on Standby mode and is trying to connect to the Wifi network.

Launch the APP, at the Home Screen press “Add Device” button or the  to start adding a device.




6. Set up and Pairing

At Hafele Devices menu, select "Wireless Gateway (Zigbee)".

Input Wifi password of router, and select "Next" button.

Make sure the indicator light is flashing at this step and tick on "Confirm the indicator is blinking rapidly", then select "Next" button.

*Note: - For Zigbee Wireless Gateway, please choose EZ Mode on the upper right corner of the confirm indicator blinking page, which will make the connection easier.
- Hold the reset button over 5s until the indication light flashes (red light).*



6. Set up and Pairing

HÄFELE

Once the initialize the device has been completed, press "Done" button to finish. Now you are able to find the device on the Home page.

